


- > 6200/6300/6500/6600/6700
- > DIN Power supplies
- > for operation using:
 - momentary switch
 - relay



1 x connector for 24V DC power plug

- > coaxiale power plug
- > 'center positive'
- > min. 22V
- > max. 28V
- > 2,1 x 5,5 x 10-11 mm

DIN Power Supplies	P [W]	DIN Power Supplies	P [W]
6030-DR-075	75W	6030-DR-240	240W
6030-DR-120	120W	6030-DR-480	480W

Connector for RJ45 plug (type B) connector 2 (black)

connect wires necessary only

Rail type	P *)	max. cable length per diameter		
		0,75mm ²	1 mm ²	1,5 mm ²
6200, 6500, 6700	45W	23m	30m	45m
6300, 6600	20W	56m	75m	112m

*) medium weight curtain, 'room' height, glider 4010, no heading

Switching	
0	<i>Open</i> and <i>close</i> should not be activated simultaneously. If so, the motorunit will switch to the programming mode
0	Pulse < 1,2 sec: - automatic complete open/close - stop
0	Pulse > 1,2 sec: the system runs untill button is released or untill the end position is reached
0	Connect every motor unit individually to the DIN power supply
0	Bounce time lower than 0,04 sec required
0	The switching current is +/- 5,5mA
0	24V out pin2 and pin4: max. 2,4VA 5V out pin3 and pin4
0	Potential free switching only

